INDEX

BRUSHLESS DC FAN

SUMMARY INFORMATION

Measurement of air volume and static pressure	0-1
Noise level data	0-3

DC FAN TECHNICAL INFORMATION

Part Number System of DC Axial Fan	1-1
Auto restart without output signal	1-2
Auto restart / Alarm signal (Type A)	1-3
Auto restart / Alarm signal (Type B)	1-4
Auto restart / Alarm signal (Type C)	1-5
Auto restart / Alarm signal (Type D)	1-6
Auto restart / Tachometer signal (Type A)	1-7
Auto restart / Tachometer signal (Type B)	1-8
Auto restart / Tachometer signal (Type C)	1-9
Auto restart / Tachometer signal (Type D)	1-10
Tachometer signal without auto-restart	1-11
PWM speed control	1-12
General specifications	1-13

DC AXIAL FAN

25x25x10 mm	KF0210-02	2-1
30x30x10 mm	KF0310-01	2-2
35x35x10 mm	KF0B10-01	2-3
40x40x10 mm	KF0410-01	2-4
40x40x10 mm	KF0410-03、08	2-5
40x40x15 mm	KF0415-11	2-6
40x40x20 mm	KF0420-01、04	2-7
40x40x28 mm	SF0428-11	2-8
40x40x28 mm	KF0428-12	2-9
40x40x28 mm	KF0428-11	2-10
50x50x10 mm	KF0510-01	2-11
50x50x15 mm	JF0515-01	2-12
60x60x10 mm	KF0610-01	2-13
60x60x15 mm	KF0615-01	2-14
60x60x15 mm	KF0615-02	2-15
60x60x15 mm	KF0615-03	2-16
60x60x15 mm	JF0615-00	2-17
60x60x20 mm	KF0620-01	2-18
60x60x20 mm	JF0620-00	2-19
60x60x25 mm	JF0625-00	2-20
60x60x25 mm	JF0625-01	2-21
60x60x25 mm	JF0625-02	2-22
60x60x38 mm	JF0638-11	2-23
70x70x15 mm	KF0715-01	2-24
70x70x25 mm	DF0725-11	2-25
80x80x10 mm	DF0810-11	2-26
80x80x15 mm	JF0815-03	2-27
80x80x20 mm	KF0820-01	2-28
80x80x25 mm	SF0825-11	2-29
80x80x25 mm	KF0825-11	2-30
80x80x25 mm	JF0825-01	2-31
80x80x25 mm	JF0825-02	2-32
80x80x25 mm	JF0825-00	2-33
80x80x38 mm	KF0838-11	2-34
80x80x38 mm	JF0838-11	2-35
92x92x25 mm	KF0925-11	2-36
92x92x25 mm	JF0925-00	2-37
92x92x38 mm	KF0938-11	2-38
120x120x25 mm	JF1225-00	2-39
120x120x25 mm	KF1225-02	2-40
120x120x25 mm	KF1225-01	2-41
120x120x38 mm	JF1238-19	2-42
120x120x38 mm	JF1238-13	2-43
120x120x38 mm	JF1238-14	2-44
140x140x25 mm	JF1425-12	2-45
140x140x25 mm	JF1425-01	2-46
140x140x25 mm	KF1425-11	2-47
200x200x30 mm	DF2030-11	2-48

DC BLOWER FAN

50x50x15 mm	WF5015-11	2-49
75x75x30 mm	WF7530-11	2-50
97x94x33 mm	WF9733-11	2-51

AC FAN TECHNICAL INFORMATION

Part Number System	3-1
General specifications	3-2

AC AXIAL FAN

80x80x25 mm	JA0825-0N	4-1
80x80x25 mm	RA0825-3N	4-2
80x80x38 mm	JA0838-0N	4-3
80x80x38 mm	RA0838-1N	4-4
92x92x25 mm	JA0925-0N	4-5
92x92x25 mm	RA0925-1N	4-6
92x92x38 mm	RA0938-1N	4-7
120x120x25 mm	JA1225-0N	4-8
120x120x25 mm	RA1225-3N	4-9
120x120x38 mm	JA1238-0N	4-10
120x120x38 mm	KA1238-1N	4-11
172x150x51 mm	JA1751-0N	4-12

FAN ACCESSORY

Metal Fan Guard	5-1
Plastic Fan Guard	5-4
Metal Fan Filter	5-5
Plastic Fan Filter 6,8 cm	5-6
Plastic Fan Filter 9,12 cm	5-7
Power Cord	5-8

APPENDIX

Reference List of Measure Unit	6-1